


1-Port Serial RS232 ExpressCard  
Part no. ANEXPSS1P



Pin no.	RS232 DB9 Male
1	DCD
2	RXD
3	TXD
4	DTR
5	GND
6	DSR
7	RTS
8	CTS
9	RI



The serial RS232 ExpressCard, easily adds an additional serial COM port to any modern laptop. It is designed based on a single-chip architecture for greater performance, reliability and reduced power consumption and CPU load.

This serial ExpressCard is made for a 34mm ExpressCard slot but will also fit in a 54mm slot. Providing optimal communication with RS232 serial devices, the serial RS232 ExpressCard supports data transfer rates of up to 460Kbps and easy installation, saving time and hassle.

**Please download drivers for this product at:**

**[www.USconverters.com](http://www.USconverters.com)**

SPECIFICATIONS	
Model number	ANEXPSS1P
Operating system	Windows 98Se, ME, 2000, XP32/64, Vista 32/64, Server 2003/8 32/64, Windows 7 32/64, Linux, MAC
Baud rate	Up to 460Kbps
Chipset	Prolific
Interface	RS232: DB9 male connector
RS232 signals	DCD, RXD, TXD, DTR, GND, DSR, RTS, CTS, RI
Compatibility	34 & 54mm ExpressCard slot
Flow control	Automatic. No IRQ Conflicts, no IRQs, IO or DMA required
Data framing	5-, 6-, 7- and 8-bit
Compliance	ExpressCard/34mm 1.0 Type II
Port mapping	Supports re-map function for legacy ports
Current draw	<100mA
Standards	Serial: EIA/TIA RS-232C
Certifications	CE, FCC, RoHS
Operating Temp.	-40 to 85°C
Operating humidity	5% To 95% - No Condensation
Warranty	5-year Limited Warranty
ECCN	4A994.a
Schedule B	8471.80.1000
HTS	8517.18.0050

Application example: Serial communication via ExpressCard.



To access technical support, please visit the U.S. Converters website at:  
[www.USconverters.com](http://www.USconverters.com)  
Here you will find:

- Latest drivers and updates for download
- Technical tips
- Documentation
- Configuration support
- and much more...

Feel free to contact our technical support team at [mail@usconverters.com](mailto:mail@usconverters.com) with any issues.

Copyrights © U.S. Converters